

Response Tags and Attributes

<environment>	The condition under which the client is being run; either PRODUCTION, DEVELOPMENT, INACTIVE, TEST, STOPPED, or ARCHIVED

<helpurl>	Points to the URL for the message board displayed by the hive in the above environment.

<user>	Container for user-specific information.
user_name (user_id)	A short string user for the user key.
full_name	The first and last name of the user.
password	The password of the user.
project	(defined below)
param	A name / value pair that can be used to give more information about a user.
name	A name that describes how the param tag is used.
admin	Indicates whether or not the user is an admin.

<project>	Container for the projects associated with the user.
id (project_id)	A unique string to identify a project
name	The human-readable name of the project
key	The key used to manage identified data of the project.
wiki	A URL for information about the project.
role	One tag for each role associated with the project.
param	A name / value pair that can be used to give more information about a project.
name	A name that describes how the param tag is used.

<cell_datas>	Contains information about the cells a user has access to.
id (cell_id)	A unique identifier for the cell.
name	The name of the cell.
url	The location of the cell.
param	A field that can be used to give more information about a cell.

- *<cell_datas> cannot be null.*

<global_data>	Data which can be used by any of the cells, but is not specific to any individual cell, such as a database connection. Global_data is for additional variables associated with a particular domain.
param	A field that can be used to give more information about a cell.